



INTELSAT 10 DSTV DECODER INSTRUCTIONS

Settings for **SONLIFE** Channel are as follows:

- 1) Press Menu Button'
- 2) Move down to 'Advanced Options' press OK
- 3) On 'Dish Installation press OK
- 4) Enter pin code 9949
- 5) Move down to 'Network2', use your right arrow key to select 'other', press OK
- 6) On 'Frequency' press OK and enter digits 12682, press OK
- 7) Move down to 'Symbol Rate' press OK enter digits 26657, press OK
- 8) Move to FEC, use right arrow key to select $\frac{1}{2}$
- 9) Move down to 'Polarization', and use right arrow key to select 'Horizontal'
- 10) On 'use NIT' select 'YES'
- 11) Move Down to accept all to 'Accept All Displayed Values And Leave Screen' then press OK.
- 12) Go to Network 3 and use your right arrow key to select other
- 13) On frequency press OK and enter the digits 12562, press OK
- 14) Move to Symbol Rate , press OK ENTER DIGITS 26657, PRESS OK
- 15) Move to FEC, use your right arrow key to select $\frac{1}{2}$
- 16) Move down to 'Polarization' use your right arrow key to select 'Horizontal'
- 17) On use NIT, select YES
- 18) Move down to accept all displayed Values and Leave Screen', thereafter , press OK

- 19) On scan all networks, press OK
- 20) Go to Network 4 and use your right arrow to select other
- 21) On frequency press OK and after the digits 12602, press OK
- 22) Move to Symbol Rate, press OK ENTER DIGITS 26657,PRESS OK
- 23) Move to FEC use your right arrow key to select ½
- 24) Move down to 'Polarization' use your right arrow key to select 'Vertical'
- 25) On use NIT, select YES
- 26) Move down to accept all displayed values and leave Screen, thereafter, press OK
- 27) On scan all networks, press OK

After scanning, press the TV channel, move down to Public Bouquet 7/10, press ok.

Surf channels as per usual p+/ p- buttons